# **DisplayFusion Monitor Profiles**

DISPLAYFUSIONBINARYFORTRESS

## **DisplayFusion Monitor Profiles**

DisplayFusion Monitor Profiles store your various monitor configurations for easy transition. This is ideal for laptop users who may have different monitor setups at home, work, etc.

#### Create a Monitor Profile

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).





	_		-	
Save Profile 🔹	Load Profile	<ul> <li>Manage Monitor Profiles</li> </ul>	Auto-split Eyefinity and nVic	lia Surround monitors
11 Monitors Gaming Work with Chat New Profile	2			
🛄 2. BenQ GL2450	H @ NVIDIA GeForce G	iTX 1660 Ti (1080x1920, 60hz, 32-bit,	100%) 🔻	Identify
2. BenQ GL2450	H @ NVIDIA GeForce G - - - - 788x1024 - - 720x1280	TX 1660 Ti (1080x1920, 60hz, 32-bit, - 1000x1920, 7000x1920, 7000x190, 7000x1900, 7000x190, 7000x190, 7000x190, 7000x190, 7000x190, 7000x1900,	100%) • • • • • • • • • • • • • • • • • • •	Identify
2. BenQ GL2450     600     600     600     600     600     600     600     600     600	H @ NVIDIA GeForce G 	TX 1660 Ti (1080x 1920, 60hz, 32-bit, 	100%) • • • • • • • • • • • • • • • • • • •	Identify
2. BenQ GL2450     400-60     Monitor Resoluti Disable	H @ NVIDIA GeForce C 7200-1284 on: 1080x1920 ✓ Enabled	TX 1660 Ti (1080x 1920, 60hz, 32-bit, 1000x 1920, 60hz, 32-bit, 1000x 1920, 1000x 1900x 1920, 1000x 1920, 1000x	100%) • •	Identify
2. BenQ GL2450     400 000     Monitor Resoluti     Disable     Set as Primary	H @ NVIDIA GeForce C	TX 1660 Ti (1080x 1920, 60hz, 32-bit, 1090x 1920, 60hz, 32-bit, 1090x 1920, 60hz, 32-bit, 1090x 1920,	100%)  V	Identify 2 S Color Depth: 32-bit Splits and Padding
2. BenQ GL2450     400 000     Monitor Resoluti     Disable     Set as Primary se these Features w	H @ NVIDIA GeForce C	TX 1660 Ti (1080x 1920, 60hz, 32-bit, 	100%) ▼ 90% - 59.844 - 59.844 Refresh Rate: 60hz ▼ ▼	Identify 2 S Color Depth: 32-bit Splits and Padding
2. BenQ GL2450     4000     4000     Monitor Resoluti     Disable     Set as Primary se these Features w     Screen Savers	H @ NVIDIA GeForce C Total Control Co	TX 1660 Ti (1080x 1920, 60hz, 32-bit, 	100%) V	Identify 2 Color Depth: 32-bit Splits and Padding Aonitor Fading

- Click the "Save Profile" button and choose "New Profile."
- Enter a name for the Profile and click OK.

#### Modify a Monitor Profile

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).

 Configure your monitors and click the "Apply" button to test your settings.





and a consideration - Display and	Pro 10.0 (Beta 16)	
Save Profile   Load Profile	Manage Monitor Profiles     Auto-split Eyef	finity and nVidia Surround monitors
11 Monitors Gaming Work with Chat New Profile		122450H
2. BenQ GL2450H @ NVIDIA GeFore	e GTX 1660 Ti (1080x1920, 60hz, 32-bit, 100%)	▼ Identify ∂
- 768x1024 - 720x1280 - 600x800 - 480x640	Sohz - 1050x192 - 1024x1280 - 1024x1280	• - 32-bit • - 60hz
- 720x 1280 - 720x 1280 - 480x 640 Monitor Resolution: 1080x1920	91.944 rz 2010 - 11000-11800 - 11020-11800 - 11020-11800 - 11020-11800 - 11020-11800	: 60hz Color Depth: 32-bit
		60hz Color Depth: 32-bit
Monitor Resolution: 1080x1920 Disable Set as Primary Orie	1024+1280     128     12	Color Depth: 32-bit
Monitor Resolution: 1080x1920 Disable Set as Primary Ise these Features with Split Monitors –	1020+1220     1020+120	Image: Solution of the second seco
Monitor Resolution: 1080x1920 Disable Set as Primary Orie Set hese Features with Split Monitors - [3] Strene Savers Use these Features with Split Monitors - [3] Strene Savers	No.44, 1280     No.44, 12	Color Depth: 32-bit Splits and Padding

- Click the "Save Profile" button, then select the Monitor Profile that you want to overwrite.
- Click Yes on the confirmation prompt.

#### **Rename a Monitor Profile**

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).



• Click the "Manage Monitor Profiles" button.

Manage Monitor Profiles	Auto-split Eyefinity and nVida	Surround monitors
10 100 10 /00 100 Tol 11	Daily GE24	450H
920x1080, 144.003hz, 32-bit, 100%)	)	Identify 🖓
- 1680x1050 - 1680x1050 - 1280x1024		●- 32-bit
-	Refresh Rate: 144.003hz	Color Depth: 32-bit
	¥	Splits and Padding
ion: 📧 Landscape	•	
	920x1080, 144.003hz, 32-bit, 100%	920x1000, 144.003hz, 32-bit, 100%)

• Select the Monitor Profile you'd like to rename and click the "Rename" button.

👸 Manage Monitor I	Profiles • DisplayFusion	Pro 10.0 (Beta 16)						
🔀 🛛 Wallpaper 🖡	Profile 🔻 🚟	Desktop Icon Profi	le 🔻 🕀 Wind	ow Position Profile 🔹	Audio De	vices 🔻 🗔	Key Combination	•
Monitor Profile	Attached Monitors	Wallpaper Profile	Desktop Icon Profile	Window Position Profile	Audio Devices	Key Combination		
11 Monitors	2/2	-	-	-	-	-		
Gaming	2/2	Gaming		Steam	-	÷		
Work with Chat	2/2	Work		Work	-			
③ Help ▼						Bename	Delete Clo	se
<u> </u>								_

• Enter a new name for the Monitor Profile and click OK.

#### **Delete a Monitor Profile**

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).

8	DisplayFusion Pro 10.0 (Beta 16)				
K	Desktop Wallpaper				
	Monitor Configuration				
K	Desktop Wallpaper Settings	•			
	Monitor Profiles	•			
_	Multi-Monitor Taskbar	•			
⊞	Window Position Profiles	•			
000	Desktop Icon Profiles	•			
<b>;</b>	Screen Saver	•			
d)	Audio Devices	•			
~	Task Manager				
<u>3</u>	Settings				
	Language	•			
?	Help				
i	About				
[→	Exit			10:26 AM	
ata	👉 Monitor Con 🔨	- E- I	£ 😳	2022-06-16	

• Click the "Manage Monitor Profiles" button.

iave Profile   Load Pro	file   Manage Monitor Pro	files 🗌 Auto-split Eyefi	nity and nVidia Surroun	d monitors
etected Profile: Gaming				
A MARKAN AND AND AND AND AND AND AND AND AND A	form	Annual		
And Annual Annua				
Abox				
	- but stand	Bangaring + Min Rosenting - Min Robert - Rosenting Robert - Rosenting Robert - Rosenting Robert - Rosenting Robert - Robert - Rob	))	
Abor IIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIII			6	
	Ena rea	12 <sup>-</sup>	100 200 200 100 -	
Junki		Re	0 GL2450H	
Citits				- 444
🖵 1. Unknown @ Intel(R) UHD G	raphics (1920x1080, 144.003hz, 32-bit,	100%)	•	dentify 🖉
1. Unknown @ Intel(R) UHD G	raphics (1920x1080, 144.003hz, 32-bit,	100%)	• •	dentify 🔁 🧭
1. Unknown @ Intel(R) UHD Gr	raphics (1920x1080, 144.003hz, 32-bit,	100%)	•	dentify 2
1. Unknown @ Intel(R) UHD Gr	raphics (1920x1080, 144.003hz, 32-bit,	100%) • 1920x10 • 1980x109	• - 144.003h	dentify
1. Unknown      Intel(R) UHD G     102 br     102	aphics (1920x1000, 144.003hz, 32-bit, - 12800x1024	100%)	• 144,003hz	dentify
1. Unknown © Intel(R) UHD Gi     00000     0000     00000     00000	aphics (1920x1080, 144.003hz, 32-bit, 1920x1080, 144.003hz, 32-bit, 1920x700, 1021 1920x700, 1021 1920x700, 1021 1920x700, 1021 1920x700, 1021 1920x700, 1920x70, 1920x700, 1920x70, 1920x70, 1920x70, 1920x700, 1920x700, 1920x700, 1	100%) - 1920x1080 Refresh Rate:	• II	dentify
1. Unknown © Intel(R) UHD G     0004078     0004078     Monitor Resolution: 1920x108     Disable     ✓ Enablec	aphics (1920/1080, 144,003hz, 32-bit, 1000/700 1000/70	100%) 90.0004/r 1920x1000 Refresh Rate:	• II	dentify
1. Unknown © Intel(R) UHD G      000000      000000      000000      000000	aphics (1920, 1080, 144,003hz, 32-bit, 1000, 144,000, 14	100%) (00%) (0000000 (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (0000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (00000000) (000000000) (000000000) (0000000000		dentify
1. Unknown © Intel(R) UHD G      000 000 000 000 000 000 000 000	aphics (1920/1080, 144.003hz, 32-bit, 1 000/000 000 000 000 0 000 000 000 000 0 000 00	100%) (00%) (19200000) (19200000) (19200000) (19200000) (1920000) (1920000000) (192000000) (192000000) (1920000000000000)	II     III     II     III     II     II     II     II     II     II     II     II     II	dentify
I. Unknown © Intel(R) UHD G  One of the second sec	aphics (1920/1080, 144.003hz, 32-bit, 1 000/000000000000000000000000000000000	100%)	Id     Id	etentify
1. Unknown © Intel(R) UHD G	aphics (1920z1080, 144.003hz, 32-bit,	100%) I 100%) I 100%) I 100%) I 100% I 10	Additional and the second	dentify Control Contro

• Select the Monitor Profile you'd like to rename and click the "Delete" button.

👸 Manage Monitor I	Profiles • DisplayFusion	Pro 10.0 (Beta 16)						
🔀 🛛 Wallpaper F	rofile 🔹	Desktop Icon Profi	le 🔻 🖽 Wind	ow Position Profile 🔹 <	10 Audio D	evices 🔹 📼	Key Combina	tion 🔻
Monitor Profile	Attached Monitors	Wallpaper Profile	Desktop Icon Profile	Window Position Profile	Audio Devices	Key Combination		
11 Monitors	2/2		+		-	-		
Gaming	2/2	Gaming	1 C	Steam				
Work with Chat	2/2	Work		Work	-	-		
0.00								
(?) Help 🔻						Rename	Delete	Close

• Click Yes on the confirmation prompt.

### Assign a Key Combination to a Monitor Profile

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).

Click the "Manage Monitor Profiles" button.

6	DisplayFusion Pro 10.0 (Beta 16)	
×	Desktop Wallpaper	
	Monitor Configuration	
X	Desktop Wallpaper Settings	•
	Monitor Profiles	•
	Multi-Monitor Taskbar	•
⊞	Window Position Profiles	•
000	Desktop Icon Profiles	►
<b>:</b>	Screen Saver	۲
d»	Audio Devices	۲
<u>~</u>	Task Manager	
ø	Settings	
<b>A</b> 2	Language	•
3	Help	
í	About	
(→	Exit	
data	Monitor Con ^	6

ave Profile   Load Profile	Manage Monitor Profiles	Auto-split Eyefinity and nVidia Sur	round monitors
etected Profile: Gaming			
	2 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		
A A Unkno		in in in it is a second	
1. Unknown @ Intel(R) UHD Graph	hics (1920x1080, 144.003hz, 32-bit, 100%)	•	Identify
1/200X / 2/0 102.4x.768 800x.600 640x.480 320x.200	9-1920x1080 	9-144.003hz	●-32-bit
4000/120 4000/480 Monitor Resolution: 1920x1080	9-1920x1080 - 1680x1050 	60.0041hz Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resolution: 1920x1080	1920x1080     1920x1050     1920x1050     1280x1024     1280x1024     1280x1024	eouodh: Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resolution: 1920x1080 Disable Set as Primary Or	ientation:	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resolution: 1920x1080 Dicable ✓ Enabled Set as Primary Or ethese Features with Split Monitors	Image: Second	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resolution: 1920x1080 Disable Set as Primary or these Features with Split Monitors ] Screen Savers	I I I I I I I I I I I I I I I I I I I	Refresh Rate: 144.003hz	Color Depth: 32-bit

• Select the Monitor Profile to which you'd like to assign a key combination.

									-
🕺 🛛 Wallpaper I	Profile 🔻 🚟	Desktop Icon Profi	le 🔻 🔠 Windi	ow Position Profile 🔹	Audio De	vices 🔻		Key Combination	
Aonitor Profile	Attached Monitors	Wallpaper Profile	Desktop Icon Profile	Window Position Profile	Audio Devices	Key Combination		Set Key Combination	
11 Monitors	2/2		+	-	-	-	×	Clear Key Combination	
Garning	2/2	Gaming	÷	Steam	-				
Work with Chat	2/2	Work	÷	Work	-	-			
									-
						Provenue		Delete Class	

 Click the "Key Combination" button and choose "Set Key Combination."

Monitor Profile	Attached Monitors	Wallpaper Profile	Desktop Icon Profile	Window Position Profile	Audio Devices	Key Combinatio	an
11 Monitors	2/2	-	-		-	-	
Gaming	2/2	Gaming	1 C	Steam	- C		
Work with Chat	2/2	Work		Work	-	-	
			🕄 Load Monitor Profile	11 Monitors • DisplayFusion	n ×		
			5 1.6	16 16			
			shift Ctrl	alt alt			
				<ul> <li>Remov</li> </ul>	re		
			Select modifiers then pr	ess desired key			
			Help •	OK Car	icel		
		L					

#### Add a TitleBar Button for a Monitor Profile

You can add a button in Windows title bars to quickly load a Monitor Profile without needing to access a DisplayFusion menu.

 Open the DisplayFusion Settings window by rightclicking the DisplayFusion tray icon and clicking "Settings."

Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager Settings Language Help About Exit	*		10:26 /	ΔM
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager Settings Language Help About	<pre></pre>			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager Settings Language Help	* * * * *			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager Settings Language	* * * * * *			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager Settings	* * *			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices Task Manager	• • • • •			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver Audio Devices	* * * * * *	-		
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles Screen Saver	* * * *			
Multi-Monitor Taskbar Window Position Profiles Desktop Icon Profiles	* * *			
Multi-Monitor Taskbar Window Position Profiles	*			
Multi-Monitor Taskbar	۲			
Monitor Profiles	۲			
Desktop Wallpaper Settings	•			
Monitor Configuration				
Desktop Wallpaper				
DisplayFusion Pro 10.0 (Beta 16)				
	DisplayFusion Pro 10.0 (Beta 16) Desktop Wallpaper Monitor Configuration Desktop Wallpaper Settings Monitor Profiles	Desktop Wallpaper Monitor Configuration	Desktop Wallpaper Monitor Configuration	DisplayFusion Pro 10.0 (Beta 16) Desktop Wallpaper Monitor Configuration

•

section.

• Click the "Functions" tab and ensure the "Enable TitleBar Buttons" checkbox is enabled.

Scroll down in the Functions list and select your

Monitor Profile from the "Monitor Configuration"

Options		510
II Functions	Custom Function	Edit Delete
Triggers	Enable Key Combinations	filter
- Taskbar	Name	Key Combination 🔛 🔚 🔚
Windows 10	Pause Desktop Wallpaper Slideshow	
Sa Windows Lock Screen	E3 Reload Current Wallpaper Profile	
C Screen Saver	Toggle Website Wallpaper Mouse/Keyboard Input	
Monitor Fading	- Monitor Configuration	~
Window Snapping	Cal Load Monitor Profile: 11 Monitors	-
Window Management	Coad Monitor Profile: Work with Chat	- 62
A Moure Management	Cal Load Next Monitor Profile (alphabetically)	
	Read Previous Monitor Profile (alphabetically)	
	- Audio Devices	~
Window Position Profiles	QUI Set Next Playback Communications Device as Default	-
Desktop Icon Profiles	80 Set Next Recording Communications Device as Default	
2 Remote Control	don Set Next Recording Device as Default	
① Compatibility	Add TilePer Dutter Add to long List	Prost All Eventions
Languages	Add Integal Button Add to Jump List	Clear Air Key Combinations
License Key	Enable TitleBar Buttons (show these buttons on each window	v)
Our Apps	Condense Integar buttons to take up less space	
/> Froubleshooting		
(i) About	Drag the TitleBar Buttons to re-order them	

😭 Settings • DisplayFusion Pro 10.0 (Beta 16) Options Edit Delete H Functions Enable Key Combinations filter... E Triggers Key Combination 🛗 🗮 🔚 ^ Name - Taskbar Tanie © Pause Desktop Wallpaper Slideshow EG Reload Current Wallpaper Profile © Toggle Desktop Wallpaper Feature © Toggle Website Wallpaper Mouse/Keyboard Input Windows 10 28 Windows Lock Screen 😔 Screen Saver - Monitor Configuration III Monitor Fading Monitor Configuration
 Load Monitor Profile 11 Monitors
 Load Monitor Profile Gaming
 Load Monitor Profile Work with Chat
 Load Next Monitor Profile (alphabetically) 🕀 Window Snapping - Window Management 🖰 Mouse Management Tail Load Next Montor Profile (alphabetically) Tail Load Previous Montor Profile (alphabetically) — Audio Devices (IIII Set Playback Communications Device as Default (IIII Set Next Playback Device as Default Gas Set Next Recording Communications Device as Default Gas Set Next Recording Device as Default 🔁 Alt+Tab H Window Position Profiles Desktop Icon Profiles 2 Remote Control Add TrifeBar Button Add to Jump List Reset All Functions Clear All Key Combinations () Compatibility Languages 🔑 License Key X Condense TitleBar Buttons to take up less space Our Apps 🔑 Troubleshooting Drag the TitleBar Buttons to re-order them (i) About (?) Help ▼ 🚺 🎯 🎔 🛅 Advanced Settings OK Cancel Apply

Click "Add TitleBar Button."

 Select the TitleBar Button Image Set, the TitleBar Button Image, and click OK.

Options	Curtam Sunction	Edit Delete		
Functions		Eure Delete		
Triggers	Enable Key Combinations	filter		
🚥 Taskbar	Name	Key Combination 📑 🔚 🔚 🕯		
Windows 10	Rause Desktop Wallpaper Slideshow			
2a Windows Lock Screen	EB Reload Current Wallpaper Profile -			
🕑 Screen Saver	Toggle Website Wallpaper Mouse/Keyboard Input -			
Monitor Fading	🖇 Edit TitleBar Button • DisplayFusion Pro 10.0 (Beta 16)	× ~ ~		
🕀 Window Snapping	Tal-Day Dutter January Cat	te:		
🚍 Window Management 🛛	Windows Aero	•		
🖰 Mouse Management	TitleBar Button Image:			
🔁 Alt+Tab	Windows Aero - Load Monitor Profile #1	• • • •		
H Window Position Prof				
Desktop Icon Profiles	⑦ Help ▼ Default OK	Cancel		
옾 Remote Control	@01 Set Next Recording Device as Default	-		
Compatibility	Add TitleBar Button Add to Jump List Reset All Functions	Clear All Key Combinations		
Languages	V Cashle TalaPas Putters (show there butters an each window)			
🖉 License Key	Condense TitleBar Buttons to take up less space			
Our Apps				
🥬 Troubleshooting				
(i) About	Drag the TitleBar Buttons to re-order them			

• Click Apply.

#### Auto-Loading Wallpaper and Desktop Icon Profiles

DisplayFusion can be configured to automatically load a Wallpaper Profile or Desktop Icon Profile when a specific Monitor Profile is loaded or detected. This is especially helpful if Windows moves your Desktop Icons around on restarts.

As soon as DisplayFusion starts up and detects your previously saved Monitor Profile, it will automatically load the associated Wallpaper and Desktop Icon Profiles without intervention.

 Open the DisplayFusion Monitor Configuration window by right-clicking the DisplayFusion tray icon and clicking "Monitor Configuration" (also accessible via the Options tab in Settings).



• Click the "Manage Monitor Profiles" button.

	Load Profile 🔻	Manage Monitor I	Profiles	Auto-split Eyefinity and nVidia	Surround monitors
etected Profile: C	iaming				
	Colors				
Abos					
		- 20			
Abor					
				2/10 Arrist Arrist Arrists	
	Linknow			BanO Gl 24	രവ
	0102000011				uerou u
🗆 1. Unknown @	Intel(R) UHD Graphics (192	0x1080, 144.003hz, 32-t	bit, 100%)	•	ldentify 🖉
				0	
				•	۲
320x	1280 1024	1280	- 192	50.00 <b>14</b>	• 32-4
320x200	- 1280x720 - 1024x768 - 1024x768 - 800x600 - 640x480		1920x108	0-144.003h	●-32-bit
Monitor Resoluti	- 1280x720 - 1280x720 - 1024x768 - 800x600 - 800x600 - 10220x1080		1920x1080 1680x1050	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resoluti	ion: 1920x1080		●-1920x1080 1680x1050	144.003 hz Refresh Rate: 144.003 hz	© N Street Sepirits and Padding
Monitor Resoluti Disable Set as Primary	ion: 1920x1080	1280x1024	● 1920x1080 ► 1680x1050	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resoluti Disable Set as Primary		n: Ca Landscape	●-1920x1080 ► 1920x1050	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resoluti Disable Set as Primary e these Features w	in: 1920x1080 ✓ Enabled Orientation th Split Monitors	n: Ca Landscape	●-1920x1080 - 1680x1050	Refresh Rate: 144.003hz	Color Depth: 32-bit
Monitor Resoluti Disable Set as Primary e these Features w S Screen Savers	and a second se	n: 🖾 Landscape	- 1920x1080	Refresh Rate: 144.003hz	Color Depth: 32-bit

• Select the Monitor Profile to which you'd like to assign a Wallpaper or Desktop Icon Profile.

 Click the "Wallpaper Profile" or "Desktop Icon Profile" button, and choose the appropriate Wallpaper or Desktop Icon Profile.

Gaming     vitos     Welpaper Profile     Deutop icon Profile     Window Position Profile     Audio Deuces     Ky Combination       W look     -     -     -     -     -     -       W look     -     -     -     -     -       W rever wark volt     2 / 2     Work     -     -     -	
24 Work	
K Clar Vallague Polla Gaming - Zeem Urrorr.with Chit Z/Z Werk - Work	
j™orr.wm.ruwr_272─── Work - Work	

#### Loading Monitor Profiles via Command Prompt

If you need to load a Monitor Profile via the command line, you can use displayfusioncommand.exe (located in the directory where DisplayFusion is installed).

The command is as follows:

displayfusioncommand.exe -monitorloadprofile "profile name"



#### Loading a Monitor Profile on Startup

If you'd like to load a Monitor Profile automatically on startup, you can create a shortcut in your startup folder that will run the command in the previous section.

For the full set of instructions, see Loading a Monitor Profile on Startup.

#### **Advanced Settings**

There are a few Monitor Configuration related settings in the DisplayFusion Settings > Advanced Settings window. The most useful one is the option to disable the confirmation prompt when changing monitor settings. If you switch Monitor Profiles often, you may wish to disable this prompt to make the process easier.

Note: If for some reason your monitors are unusable after a settings change, DisplayFusion won't be able to revert back to the original settings if the confirmation prompt is disabled. You'd likely need to reboot your machine to make the displays usable again.

 Open the DisplayFusion Settings window by right-clicking the DisplayFusion tray icon and clicking "Settings."



Click the Advanced Settings button.

👪 Settings • DisplayFusion Pro 10	0 (Beta 16)				
(i) Options	Ontines				
til Functions	Start with Windows		Monite	or Configuration	
E Triggers	Show in Windows desktop context menu		Deals	ten Mellenen	
🚥 Taskbar	Default Tray Icon Behavior:		Desk	top waiipaper	
Windows 10	Open DisplayFusion Desktop Wallpaper			•	
28 Windows Lock Screen					
📑 Screen Saver	Update Check				
III Monitor Fading	Check for Updates Automatically		Check f	for Updates Now	
Window Snapping	Check for new Beta (newer, Unstable) Versions		Internet C	onnection Settings	
🚍 Window Management					
🖰 Mouse Management	My Binary Fortress Account				
∂ Alt+Tab	Email Address:			Login	
H Window Position Profiles	Password:			Register	
Desktop Icon Profiles	Login to retrieve your License Ke	y and sync with your Binary Fortres	Account.	Reset Password	
2 Remote Control	-				
① Compatibility	Ineme			_	
Languages	👷 Light mode			•	
🖉 License Key					
'#' Our Apps					
Troubleshooting					
(i) About	Show Welcome Wizard	Export Settings	0	Restore Settings	
⑦ Help ▼ 6 0 ¥ in		Advanced Settings O	ĸ	Cancel Apply	-

• Search for and double-click "Don't Show Confirmation Prompt" Setting.

Only show modified values	don't show	
Setting	Value	1
- Desktop Icons		
Don't Show Confirmation when Loading Profile		
Don't Show Overwrite Confirmation when Saving Profile		
Don't Show Success Notification when Saving Profile		
General		
Don't Check nVidia Processes		
Don't Show Error Messages for HotKey Bind Failures		
Don't Show Tray Icon Notification Balloons		
Languages: Show Language File Errors		
- Monitor Configuration		
Don't Show 'different number of monitors' Prompt		
Don't Show Confirmation Prompt		
Don't Show Confirmation Prompt (command line and API loa	ding only)	
Don't Show Error When Load Monitor Profile Fails		
Don't Show Live Monitor Preview		
Always Show Preview Window Text		
Disable Show Desktop on Hover (only show on click)		
Don't Force to Bottom when Screen Saver is Detected		
Don't Load External Start Button Data		
Don't Load System Jump List Items		

 Select "Confirmation prompts are not shown" and click OK.

舒 Edit Advanced Setting • DisplayFusion Pro 10.0 (Beta 16)	×
Don't Show Confirmation Prompt:	
Confirmation prompts are shown (default value)     Onfirmation prompts are not shown	
🕜 Help 🔻	OK Cancel

### **About DisplayFusion**

DisplayFusion gives users power and precision over their multi-monitor setup, with automation and customization options to create the perfect displays, every time.

To learn more about DisplayFusion, visit: https://www.displayfusion.com

### **About Binary Fortress Software**

Binary Fortress has spent 18 years in pursuit of one goal: create software to make life easier. Our software ranges from display management and system enhancement utilities to monitoring tools and digital signage. IT administrators, professional gamers, coffee-shop owners, and MSPs all rely on Binary Fortress to make their days better, and their lives easier.

Copyright © 2007-2025 Binary Fortress Software, all rights reserved. The Binary Fortress logo is a trademark of Binary Fortress Software. The DisplayFusion logo is a trademark of Binary Fortress Software.

Binary Fortress Software 1000 Innovation Drive, Suite 500 Kanata, Ontario, Canada K2K3E7 <u>https://www.binaryfortress.com</u>